



Software Compatibility

The CD contains the latest Remote Control Software RCS 2.0.4 and the firmware for the D-01, KM D, TLM103 D, KMR 81 D, KMS104 D and KMS105 D digital microphones as well as the firmware for the 2 channel Digital Microphone Interfaces DMI-2 and DMI-2 portable as well as the 8 channel Digital Microphone Interface DMI-8 and the EtherSound enabled Multi Channel Audio Interface MCA-ES.

Please note: In order to use the new features you need to update **all** Solution-D components in the sequence RCS, DMI, microphones.

Software compatibility to RCS 2.0.4 is given using the following firmware version:

Device	Software Version	File Name
D-01 (hardware version 12.02)	5.14	D-01_HW12_02_SW05_14.mfw
D-01 (hardware version 13.03)	6.05	D-01_HW13_03_SW06_05.mfw
KM D	2.13	KM D_HW01_02-04_SW02_13.mfw
TLM103 D	1.07	TLM103 D_HW01_00-01_SW01_07.mfw
KMR 81 D	1.03	KMR 81 D_HW01_02-04_SW01_03.mfw
KMS104 D	1.01	KMS104 D_HW01_02-04_SW01_01.mfw
KMS105 D	1.01	KMS105 D_HW01_02-04_SW01_01.mfw
DMI -2 (hardware version 003)	5.08	DMI2_HW003_SW05_08.dfw
DMI -2 portable	1.06	DMI2_PORTABLE_HW001_SW01_06.dfw
DMI-8 (hardware version 001)	1.38	DMI8_HW001_SW01_38.dfw
DMI-8 (hardware version 002)	1.44	DMI8_HW002_SW01_44.dfw
MCA-ES	1.00	MCA_ES_HW001_SW01_00.dfw

Update Procedure

1. Update RCS to revision 2.0.4

- exit the RCS if running
- launch 'Setup.exe' (Windows) or 'Install RCS' (Mac) from the CD and follow the instructions of the installer

2. Update the DMI-2/8

- launch RCS 2.0.4
- click 'Options' 'DMI' in the menu
- if the 'Software revision' is older than shown in the table above then update the DMI by choosing the button 'SW Update' and selecting the corresponding file from the CD

3. Update the microphone(s)

- click the button 'System' and the System window will appear
- click the button 'SW Update' in the System window and the 'SW Update' window will appear
- if the 'Version' of the applied boot partition is older than shown in the table above then choose the appropriate microphone firmware file from CD
- select the target boot partition in the 'Save To' column
- click the button 'Start Update'. The microphone firmware download needs up to 35 min
- when the download is completed close the 'SW Update' window
- after that it takes about one minute until the microphone is ready for use again. This is indicated by the Data Valid LED on the DMI-2 and the corresponding display in the RCS

Georg Neumann GmbH, February 26, 2019